

12 February 2007

ELECTROMAGNETIC PERFORMANCE OF A WIRE GRID GROUND SCREEN  
Ken Stewart, NRL, Code 7211

Recent discussions of the possible need for a ground screen beneath the LWA antennas has led to questions about requirements for the ground screen itself. This memo does not address the question of whether a ground screen will be necessary to meet LWA specifications, but only the question of how closely spaced a wire grid has to be to approximate a solid, perfectly conducting ground screen.

Figure 1 shows a section of a square wire grid used as a model for a simple ground screen consisting of thin wires of diameter  $d \ll D$ , where  $D$  is the center-to-center distance between the wires.





Figure 1. A section of the square grid ground screen used in the simulation.

Figure 2 shows a finite-integral time-domain calculation of the reflectance and transmittance of the wire grid for a plane wave at normal incidence. For this simulation the wire material was assumed to be an excellent conductor such as Cu or Al. Even a relatively poor conductor such as stainless steel, which has a resistivity 40 times that of Cu, differs significantly only above microwave frequencies, and for HF/VHF frequencies looks identical on the scale of Figure 2. This grid reflects 50% of the incident energy when the wavelength is four times the wire spacing, increasing to 90% at  $\lambda = 12D$ .



**Figure 2. Calculated reflectance and transmittance of a ground screen consisting of a square grid of thin wires.**

A specific example for the LWA, a square grid of thin ( $d = 3$  mm) wires 10 cm apart would reflect 98.7% of the incident radiation at 80 MHz, and greater than this at lower frequencies. This same ground screen, if constructed from stainless steel wires, would still reflect 98.5% of incident RF power. These calculations for thin wires at normal incidence are the worst case. For thicker wires, or for angles of incidence other than  $0^\circ$ , as would occur at points other than directly beneath an antenna, the reflectance is even higher.